

# U-Bend Compatibility List

Lamps: KT-LED15T8-U6GC-8XX-S



Check back often for updates. If the ballast you are looking for is not on this list, please contact us, and we will make every effort to evaluate compatibility.

**Note: Reduced Lamp Load is defined as operating one less lamp than the ballast is rated for.**

Ballast Description						Nominal Lamp Load		Reduced Lamp Load	
Brand	Part Number	Starting Method	Number of Lamps	Ballast Factor	Lamp Connection	Input Voltage		Input Voltage	
						120	277	120	277
Keystone	KTEB-232-UV-IS-N-P	IS	2	N	Parallel	✓	✓	✓	✓
	KTEB-432RIS-1-TP-SL	IS	4	N	Parallel	✓	—	✓	—
	KTEB-332-UV-IS-N-P	IS	3	N	Parallel	✓	✓	✓	✓
	KTEB-432-UV-IS-N-P	IS	4	N	Parallel	✓	✓	✓	✓
	KTEB-2C72-1-TP	PS	1	N	Parallel	x	x	—	—
Advance	ICN-2P32-N	IS	2	N	Parallel	✓	✓	✓	✓
	IOPA-2P32-N	IS	2	N	Parallel	✓	✓	✓	✓
	IOP-2P32-N	IS	2	N	Parallel	✓	✓	✓	✓
	IOP-2P32-LW-N	IS	2	L	Parallel	✓	✓	✓	✓
	IOPA-3P32-LW-N	IS	3	L	Parallel	✓	✓	✓	✓
	IOPA-4P32-N	IS	4	N	Parallel	x	x	x	x
	IOPA-4P32-HL-SC	IS	4	H	Parallel	✓	✓	✓	✓
	IOP-4P32-N	IS	4	N	Parallel	✓	✓	✓	✓
	IOP-4P32-LW-N	IS	4	L	Parallel	✓	✓	✓	x
	ICN-4P32-N	IS	4	N	Parallel	✓	✓	✓	x
	IOP-1P32-N	IS	1	N	N.A.	✓	✓	—	—
	IOP-2P32HL-SC	IS	2	H	Parallel	—	—	—	—
	IOPA-1P32-N	IS	1	N	N.A.	✓	✓	—	—
	ICN-1P32-N	IS	1	N	N.A.	✓	✓	—	—
	IOPA-2P32HL-SC	IS	2	H	Parallel	✓	✓	✓	✓
	REB-2P32-SC	IS	2	N	Parallel	—	—	—	—
	IOPA-3P32-N	IS	3	N	Parallel	x	x	x	x
	IOP-3P32-N	IS	3	N	Parallel	x	x	x	x
	REB-4P32-SC	IS	4	N	Parallel	✓	—	✓	—
	IOP-4P32-HL-SC	IS	4	H	Parallel	✓	✓	✓	x
	ICN-4P32-SC	IS	4	N	Parallel	✓	✓	✓	✓
	ICN-3P32-N	IS	3	N	Parallel	✓	✓	✓	✓
	IOP-2PSP32-N	PS	2	N	Parallel	✓	✓	✓	✓
	IOP-3PSP32-SC	PS	3	N	Parallel	✓	✓	✓	✓
	IOP-3PSP32-LW-SC	PS	3	L	Parallel	✓	✓	✓	✓
	IOP-4PSP32-SC	PS	4	N	Parallel	✓	✓	✓	✓
	IOP-4PSP32-LW-SC	PS	4	L	Parallel	✓	✓	✓	✓
	IOP-2S32-SC	PS	2	N	Series	x	x	x	x
	IZT-2S32-SC	DPS	2	N	Series	✓	✓	x	x
	IOP-2PSP32-LW-N	PS	2	L	Parallel	✓	✓	✓	✓
	IZT-2PSP32-SC	DPS	2	N	Parallel	x	x	x	x
Ballast Wise	DXE118M8	PS	1	N	N.A.	—	—	—	—

✓ Yes
— N/A
x No

1. SmartDrive LED Lamp Compatibility is determined when the ballast turns on the LED lamp and the electrical characteristics of the LED lamp are stable and within designed operating specifications.
2. Keystone SmartDrive LED Lamp Compatibility does not make any guarantees of electrical performance or lifetime for ballasts that are not manufactured by Keystone.
3. Ballast compatibility testing is performed with specific date codes. Please contact Keystone for more information on date code of ballasts tested.
4. All data subject to change.

Ballast Description						Nominal Lamp Load		Reduced Lamp Load	
Brand	Part Number	Starting Method	Number of Lamps	Ballast Factor	Lamp Connection	Input Voltage		Input Voltage	
						120	277	120	277
EIKO	PM-2X32T8-UNV-IS-L	IS	2	L	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS	IS	3	N	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS-H	IS	3	H	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS-L	IS	3	L	Parallel	✓	✓	✓	✓
	PM-4X32T8-UNV-IS	IS	4	N	Parallel	✓	✓	✓	✓
	PM-4X32T8-UNV-IS-L	IS	4	L	Parallel	✓	✓	✓	✓
	PM-2X32T8-UNV-IS	IS	2	N	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-PS	PS	3	N	Series	✗	✗	✗	✗
	PM-3X32T8-UNV-PS-H	PS	3	H	Series	✗	✗	✗	✗
ESPEN	VE232MVHIPE	IS	2	N	Parallel	✓	✓	✓	✓
	VE232MVHIPHE	IS	2	H	Parallel	✓	✓	✓	✓
	VE232MVHIPLE	IS	2	L	Parallel	✓	✓	✓	✓
	VE232MVHRPHT3-AB	PS	2	H	Series	✓	✓	✗	✗
General Electric	GE-232-MV-N P	IS	2	N	Parallel	✓	✓	✓	✓
	GE232MAX-N/ULTRA P	IS	2	N	Parallel	✓	✓	✓	✓
	GE432MAX-H/ULTRA P	IS	4	H	Parallel	✓	✓	✓	✓
	GE432MAX-L/ULTRA P	IS	4	L	Parallel	✓	✓	✓	✓
	GE-232-MAX-H/Ultra P	IS	2	H	Parallel	✓	✓	✓	✓
	GE432MAX-G-N	IS	4	N	Parallel	✓	✓	✓	✓
	GE132MAX-G-N	IS	1	N	n.a	✓	✓	—	—
	GE132MAX-H/ULTRA	IS	1	H	n.a	✓	✓	—	—
	GE132MAX-L/ULTRA	IS	1	L	n.a	✓	✓	—	—
	GE132MAXP-N/ULTRA	IS	1	N	n.a	✓	✓	—	—
	GE232MV-N-DIY	IS	2	N	Parallel	✓	✓	✓	✓
	GE232-120-RES	IS	2	N	Parallel	✓	—	✓	—
	GE232MAX-L/ULTRA	IS	2	L	Parallel	✓	✓	✓	✓
	GE332MV-N	IS	3	N	Parallel	✓	✓	✓	✓
	GE332MAX-N/ULTRA	IS	3	N	Parallel	✓	✓	✓	✓
	GE332MAX-L/ULTRA	IS	3	L	Parallel	✓	✓	✓	✓
	GE332MAX-G-N	IS	3	N	Parallel	✓	✓	✓	✓
	GE332MAXP-H/ULTRA	IS	3	H	Parallel	✗	✗	✗	✗
	GE432-120-RES	IS	4	N	Parallel	✓	—	✓	—
	GE432MV-N-42T	IS	4	N	Parallel	✓	✓	✓	✓
	GE432MAX-N/ULTRA	IS	4	N	Parallel	✓	✓	✓	✓
	GE-232-MV-L	IS	2	L	Parallel	✓	✓	✓	✓
	GE232-MVPS-N	PS	2	N	Parallel	✓	✓	✓	✓
	GE-332-MVPS-N	PS	3	N	Parallel	✓	✓	✓	✓
	GE432-MVPS-N	PS	4	N	Parallel	✓	✓	✓	✗
	GE432MVPS-N-V03	PS	4	N	Parallel	—	—	—	—
	GE-232-MV-PS-N	PS	2	N	Parallel	✓	✓	✓	✓
Halc	EP232IS/L/MV/SL	IS	2	L	Parallel	✓	✓	✓	✓
	E432IS/120/R/SL	IS	4	N	Parallel	✓	—	✓	—
	EP232IS/MV/HE	IS	2	N	Parallel	✓	✓	✓	✓
	EP332IS/MV/HE	IS	3	N	Parallel	✓	✓	✓	✓
	EP432IS/MV/HE	IS	4	N	Parallel	✓	✓	✓	✓
	EP432IS/L/MV/HE	IS	4	L	Parallel	✓	✓	✓	✓



Yes



N/A



No

1. SmartDrive LED Lamp Compatibility is determined when the ballast turns on the LED lamp and the electrical characteristics of the LED lamp are stable and within designed operating specifications.
2. Keystone SmartDrive LED Lamp Compatibility does not make any guarantees of electrical performance or lifetime for ballasts that are not manufactured by Keystone.
3. Ballast compatibility testing is performed with specific date codes. Please contact Keystone for more information on date code of ballasts tested.
4. All data subject to change.

Ballast Description						Nominal Lamp Load		Reduced Lamp Load	
Brand	Part Number	Starting Method	Number of Lamps	Ballast Factor	Lamp Connection	Input Voltage		Input Voltage	
						120	277	120	277
Howard Industries	EPH4/32IS/MV/SC/HE	IS	4	H	Parallel	✓	✓	✓	✓
	EP3/32IS/MV/SC/HE	IS	3	N	Parallel	✓	✓	✓	✓
	EPL4/32IS/MV/MC/HE	IS	4	L	Parallel	✓	✓	✓	✓
	EPH2/321S/MV/MC/HE	IS	2	H	Parallel	✓	✓	✓	✓
	E2/32IS-120MC	IS	2	N	Parallel	✓	—	✓	—
	EPL2/32IS/MV/MC/HE	IS	2	L	Parallel	✓	✓	✓	✓
	EPL3/32IS/MV/SC/HE	IS	3	L	Parallel	✓	✓	✓	✓
	EP4/32IS/MV/MC/HE	IS	4	N	Parallel	✓	✓	✓	✓
	EP2/32IS/MV/MC/HE	IS	2	N	Parallel	✓	✓	✓	✓
	EP3/32IS/MV/MC/HE	IS	3	N	Parallel	✓	✓	✓	✓
LumaPro	4KGH1 EB-432IS-120	IS	4	N	Parallel	✓	—	✓	—
MAXLITE	SKEU322HEL/SC	IS	2	L	Parallel	✓	✓	✓	✓
	SKEU324HE/SC	IS	4	N	Parallel	✓	✓	✓	✓
	SKEU323L/SC	IS	3	N	Parallel	✓	✓	✓	✓
	MLEU322HEL/SC	IS	2	L	Parallel	✓	✓	✓	✓
	MLEU323H/SC	IS	3	H	Parallel	✓	✓	✓	✓
	MLEU324HE/SC	IS	4	N	Parallel	✓	✓	✓	✓
Osram Sylvania	QTP 2X32T8/UNV ISN-SC P	IS	2	N	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISN-SC P	IS	2	N	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISL-SC P	IS	2	L	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISH-SC	IS	3	H	Parallel	✓	✓	✓	✗
	QHE 4X32T8/UNV ISN-SC P	IS	4	N	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV ISL-SC P	IS	4	L	Parallel	✓	✓	✓	✓
	QTP 4x32T8/UNV ISN-SC	IS	4	N	Parallel	✓	✗	✓	✗
	QHE 1X32T8/UNV ISN-SC	IS	1	N	n.a	✓	✓	—	—
	QHE 1X32T8/UNV ISL-SC	IS	1	L	n.a	✓	✓	—	—
	QTP 1X32T8/UNV ISN-SC	IS	1	N	n.a	✓	✓	—	—
	QHE 2X32T8/UNV ISH-SC	IS	2	H	Parallel	✓	✓	✓	✗
	QTP 3X32T8/UNV ISN-SC	IS	3	N	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISN-SC	IS	3	N	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISL-SC	IS	3	L	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV PSX-SC	PRS	4	L	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV PSH-HT	PRS	2	H	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV PSN-MC	PRS	2	N	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV PSN-SC	PRS	3	N	Parallel	✓	✓	✓	✓
	QTP 3X32T8/UNV PSX-SC	PRS	3	L	Series	✗	✗	✗	✗
	QTP3X32T8/UNV PSN-SC	PRS	3	N	Series	✗	✗	✗	✗
	QHE 4X32T8/UNV PSN-SC	PRS	4	N	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV DIM-TC	PRS	2	N	Series	✗	✗	✗	✗
PES	PES120ET8-12SMT-4	IS	4	N	?	✗	—	✗	—
	PES120DET8	PS	2	N	Parallel	—	—	—	—
	PES120DET8-12SMT	PS	2	N	Parallel	✗	✗	✗	✗
PLUSRITE	BAF232IS/MV	IS	2	N	Parallel	✓	✓	✓	✓
	BAF332IS/MV	IS	3	?	?	✓	✓	✓	✓
Robertson	ISU232T8120 3P20116	IS	2	N	Parallel	✓	✓	✓	✓
	RSZ132T8120	PS	1	N	n.a	✗	✗	—	—
SOLA	E-758-F-232-SC	IS	2	N	Parallel	✓	—	✓	—
	E-758-U-232-MC	IS	2	N	Parallel	✓	✓	✓	✓



Yes



N/A



No

1. SmartDrive LED Lamp Compatibility is determined when the ballast turns on the LED lamp and the electrical characteristics of the LED lamp are stable and within designed operating specifications.
2. Keystone SmartDrive LED Lamp Compatibility does not make any guarantees of electrical performance or lifetime for ballasts that are not manufactured by Keystone.
3. Ballast compatibility testing is performed with specific date codes. Please contact Keystone for more information on date code of ballasts tested.
4. All data subject to change.

Ballast Description						Nominal Lamp Load		Reduced Lamp Load	
Brand	Part Number	Starting Method	Number of Lamps	Ballast Factor	Lamp Connection	Input Voltage		Input Voltage	
						120	277	120	277
SUNPARK	120-1/32IS HPF	IS	1	N	n.a	×	—	—	—
	U-2/32IS HBF	IS	2	H	Parallel	✓	✓	✓	✓
	U-2/32ISE-LBF	IS	2	L	Parallel	✓	✓	✓	✓
	U-3/32ISE	IS	3	N	Parallel	✓	✓	✓	✓
	U-3/32ISE-HBF	IS	3	H	Parallel	✓	✓	✓	✓
	120-3/32IS MP,F	IS	3	N	Parallel	✓	—	✓	—
	U-4/32IS HP,F	IS	4	N	Parallel	✓	✓	✓	✓
	U-4/32IS HBF	IS	4	H	Parallel	✓	✓	✓	✓
	U-4/32ISE-LBF	IS	4	L	Parallel	✓	✓	✓	✓
	U-1/32PSE	PS	1	N	n.a	×	×	—	—
	U-2/32PSE	RS	2	N	?	×	×	×	×
	U-2/32PSE-HBF	RS	2	H	?	×	×	×	×
	U-232PS3	RS	2	N	?	×	×	×	×
	U-232PS3-HBF	RS	2	H	?	×	×	×	×
	SL15T	RS	2	N	Parallel	✓	—	✓	—
	LC 12011T	PS	1	?	n.a	×	—	—	—
	LC 12013T	PS	1	?	n.a	✓	—	—	—
Superior Life	70201	IS	2	N	Parallel	✓	✓	✓	×
	70210	PS	2	N	Parallel	✓	✓	✓	✓
	70211	PS	4	N	Parallel	✓	✓	✓	✓
TCP	E2P32ISUNVHE	IS	2	H	Parallel	✓	✓	✓	✓
	E4P32ISUNVLE	IS	4	L	Parallel	✓	✓	✓	×
	E3P32ISUNVE	IS	3	N	Parallel	✓	✓	✓	✓
	E3P32ISUNVLE	IS	3	L	Parallel	✓	✓	✓	✓
	E4P32ISUNVE	IS	4	N	Parallel	✓	✓	✓	✓
	E4P32ISUNVHE	IS	4	H	Parallel	✓	✓	✓	✓
Universal Lighting Technologies	B232IUNVHP-N	IS	2	N	Parallel	✓	✓	✓	✓
	B232IUNVEL-A	IS	2	L	Parallel	✓	✓	✓	✓
	B233IUNVHE-A	IS	2	N	Parallel	✓	✓	✓	✓
	B432IUNVHE L-A	IS	4	L	Parallel	✓	✓	✓	✓
	B232IUNVHEH-A	IS	2	H	Parallel	✓	✓	✓	✓
	B332IUNVHP-A	IS	3	N	Parallel	✓	✓	✓	✓
	B432IUNVHP-A	IS	4	N	Parallel	✓	✓	✓	✓
	B232I120RES-A	IS	2	N	Parallel	✓	—	✓	—
	B432I120RES-A	IS	4	N	Parallel	✓	—	✓	—
	B132IUNVHP-N	IS	1	N	n.a	✓	✓	—	—
	B432PUNVHE-A	PS	4	N	Parallel	✓	✓	✓	✓
	B232PUNVHE-B	PS	2	N	Parallel	✓	✓	✓	✓
	B332PUNVHE-A	PS	3	N	Parallel	✓	✓	✓	✓
Watran	DBG32N-MV-TP-PS-HL	PS	4	?	?	×	×	×	×
WORK HORSE	WHS4-120-T8-IS	IS	4	N	Parallel	✓	—	✓	—
	WHS4-UNV-T8-IS	IS	3	N	Parallel	✓	✓	✓	✓
	WHS4-UNV-T8-IS	IS	4	N	Parallel	✓	✓	✓	✓



Yes



N/A



No

1. SmartDrive LED Lamp Compatibility is determined when the ballast turns on the LED lamp and the electrical characteristics of the LED lamp are stable and within designed operating specifications.
2. Keystone SmartDrive LED Lamp Compatibility does not make any guarantees of electrical performance or lifetime for ballasts that are not manufactured by Keystone.
3. Ballast compatibility testing is performed with specific date codes. Please contact Keystone for more information on date code of ballasts tested.
4. All data subject to change.